



RJH Chamois CH series of double ended polishing machines.

High quality, reliable and extremely safe polisher designed for general polishing and finishing tasks in a D&T environment. Bench, pedestal and dust extraction mounted models are available, with single or three phase electrics, with or without a braking system.

## **SPECIFICATION**

DUST EXTRACTION CH2001TE 3 phase, 1500rpm CH2001SE 1 phase, 1500rpm

Weight 93 Kg

Mop Drive Motor 3 phase = 1.25 Kw, 1 phase = 0.70 Kw Electrical Supply 3 phase = 400/3/50, 1 phase = 230/1/50

Maximum Mop Size 200mm x 25mm

Dust Extractor Motor 0.55 Kw

CH2003TE 3 phase, 3000rpm CH2003SE 1 phase, 3000rpm

Weight 87 Kg

Mop Drive Motor 3 phase = 0.85 Kw, 1 phase = 0.70 Kw Electrical Supply 3 phase = 400/3/50, 1 phase = 230/1/50

Maximum Mop Size 200mm x 25mm

Dust Extractor Motor 0.55 Kw

PEDESTAL MODELS CH2001TP 3 phase, 1500rpm

CH2001SP 1 phase, 1500rpm

Weight 64 H

Mop Drive Motor 3 phase = 1.25 Kw, 1 phase = 0.70 Kw Electrical Supply 3 phase = 400/3/50, 1 phase = 230/1/50

Maximum Mop Size 200mm x 25mm

CH2003TP 3 phase, 3000rpm CH2003SP 1 phase, 3000rpm

Weight 59 K

Mop Drive Motor 3 phase = 0.85 Kw, 1 phase = 0.70 Kw Electrical Supply 3 phase = 400/3/50, 1 phase = 230/1/50

Maximum Mop Size 200mm x 25mm

BENCH MODELS CH2001T 3 phase, 1500rpm CH2001S 1 phase, 1500rpm

40 Kg

Mop Drive Motor 3 phase = 1.25 Kw, 1 phase = 0.70 Kw Electrical Supply 3 phase = 400/3/50, 1 phase = 230/1/50

Maximum Mop Size 200mm x 25mm

CH2003T 3 phase, 3000rpm CH2003S 1 phase, 3000rpm

Weight 35 Kg

Mop Drive Motor 3 phase = 0.85 Kw, 1 phase = 0.70 Kw Electrical Supply 3 phase = 400/3/50, 1 phase = 230/1/50

Maximum Mop Size 200mm x 25mm

### **KEY FEATURES**

Weight

Integral dust extractor with a tray collector for easier and cleaner waste handling Taper adaptors suitable for use with polishing mops, finishing wheels or wire brushes up to  $200 \times 25 \text{mm}$  Supplied with two  $200 \times 25 \text{mm}$  – one stitched and one loose leaf calico

## **SAFETY FEATURES**

No-volt overload push-button starter



# RJH Chamois CH Series Double Ended Polishers

110 volt control circuit

Dust extraction indicator light which lights up when the filter requires servicing

Motor thermal overload protection

Fire retardant terylene needlefelt dustbag

Heavy duty adjustable polycarbonate eye shields

Large adjustable mop guards with safe edging and 3" (approx. 76mm) extraction spigots

Excellent workpiece access

Protective sleeves on taper nose on both sides of the polishing mop

### **OPTIONAL REFINEMENTS**

Flexible halogen floodlight with transformer Lockable triple pole isolator Single phase unit Parallel adaptors Lockable "E" stop





Telephone +44 (0)1322 447611 | Email <u>sales@rk-int.com</u>